

AC-DC Switching Power Supplies

SEC-40BRM 40 Amp N+1 /w. battery back-up



High current switching power system provides N + 1 redundancy and is expandable from 40 Amps to 100 Amps.

Specifications						
Model#	Input Voltage	Output Voltage	Dimensions	Output	Fuse Rating	Shipping Weight Lbs.
SEC-40BRM	105-125 VAC 50/60 HZ	13.8 VDC	3.5 x 19 x 14	40 Amps	n/a	26

Applications
Any critical power supply application Telecommunications systems Mobile sound/audio displays GPS receivers Security systems CCTV systems

Design Features
Provides N + 1 redundancy on SEC60BRM, 80BRM, 100BRM Voltage/Amperes meter Module status LEDs, fault indicator LEDs and fault alarm are standard features on all models Highly regulated output voltage Short circuit protection and overload current